

# Calling Cards

### In this article




- [Section overview](#)
- [Advanced Search](#)
- [Creating a Card Series](#)
- [Calling Cards Series Properties](#)

## Section overview


This section represents a built-in calling cards generator that allows you to create or change cards series for prepaid customers. Each generated card is considered a billing client, so a customer can perform calls, log in to their client panel to browse statistics and other relevant information.

Screenshot: Calling Cards section main window



Column	Description
Status	A name that describes current cards series
	 Indicates that cards series is <b>active</b>
	 Indicates that cards series is <b>stopped</b>
	 Indicates that cards series is <b>deleted</b>
Number of Series   Name of Series	A code of cards series and its name (if indicated). This code will prepend a serial number (only numeric, up to 100,000,000)
Balance	Cards balance value within a current series
Qty	Quantity of cards within a series
Reseller	Name of a reseller, who owns a cards series
Rate Table	Rate table applied to respective cards series
Act. Fee	Price of cards series activation fee
Maint. Fee	Fixed charge for activated cards within a series

## Advanced Search

In the top right corner of the section above the table, the **Advanced Search** drop-down menu is located. By clicking on a red downwards arrow  icon (calling cards in the section are filtered by **Active** status and **All resellers** by default), the following drop-down menu is displayed:

Screenshot: Advanced Search drop-down menu

Status: Active

Reseller: all resellers

Rate Table:

Routing Plan:

Reset

Search

To apply the specified search criteria, click the **Search** button; to cancel the applied parameters, click **Reset**.

Creating a Card Series

To create a card series, click the **New Cards Series** button and a new window with settings will pop-up:

Screenshot: Generate cards series window

Calling Cards

SYSTEM INFORMATION

Series Name:

Series Number: 4

Balance: 5 USD

Quantity: 100

PIN length: 12 digits

Status: Active

Control Panel

NOTES

BILLING SETTINGS

Rate Table:

Tax Profile:

Routing Plan:

Activation Fee: 0 USD

Maintenance Fee: 0 USD every hours

EXPIRATION SETTINGS

Expire date:

Expire period: day(s)

OK

Cancel

Apply

Field	Description
Series Name	Indicate a name for a cards series
Series Number	Define a code of a cards series. This code will prepend a serial number (only numeric, up to 100 000 000). For example, if the <b>Series Number</b> is <b>45</b> , the cards number will start with 45:  <b>45-001122333, 45-001122334</b> and so on.
Balance	Specify the cards balance value within a current series
Quantity	Set the number of calling cards within a current series
PIN Length	Specify a PIN-code length for a current calling cards series (it can be no less than 8 digits)
Status	Define an initial status of created calling cards within a series. Can be changed later in cards series settings

<b>Control Panel</b> checkbox	Defines whether calling cards users can log in to their control panels or not. If enabled, a user can log in to the control panel by using the card serial number as login and a PIN-code as password
<b>Notes</b>	Indicate additional information regarding a cards series (optional)
<b>Rate Table</b>	Define a rate table for all cards within a series. This field is mandatory
<b>Tax Profile</b>	Select a respective tax profile that will be used for billing settings
<b>Routing Plan</b>	Select a routing plan for a current cards series
<b>Activation Fee</b>	Enter an activation fee in this field (if necessary)
<b>Maintenance Fee</b>	Define a charged fee each X hours for all activated cards
<b>Expiration date</b>	Current calling cards series will be expired on a specified date
<b>Expiration period</b>	When a specified number of days passes, starting from activation date, a current calling cards series will be expired

After specifying all necessary fields, click **OK** and a new cards series will be created.



## Calling Cards Series Properties

To open series properties, click **Series Number**, and you will be displayed a table of calling cards with the following columns:

Screenshot: *Cards List tab*

Cards List			
Status	Number	Balance	PIN
Pending	1-005668240	5 USD	9592 6160 7855
Pending	1-005668241	5 USD	7558 1233 1238
Pending	1-005668242	5 USD	1403 9455 6724
Pending	1-005668243	5 USD	3431 8613 8447
Pending	1-005668244	5 USD	6211 3961 9495

Column	Description
<b>Status</b>	Status of a card within a current series. There are <b>4</b> possible statuses: <b>activated, pending, expired, used</b>
<b>Number</b>	Number of a card within a current series
<b>Balance</b>	Balance of a respective calling card
<b>PIN</b>	Respective calling card PIN-number

1. You can export the whole card series to an **.xls** file by clicking the **Download XLS**  icon (see screenshot above).
2. You can use the **Advanced Search** drop-down menu to find a card by clicking on a blue downwards arrow  icon in the right-hand corner of the page (see screenshot above).

To change the previously entered parameters while creating a series, please open the **Edit Cards Series** tab.

Screenshot: *Edit Cards Series tab*

Cards List

Edit Cards Series

#1 Telecard [USD]

SYSTEM INFORMATION

Series Number: 1

Balance: 5 USD

Quantity: 100

Series Name: Telecard

Status: Active

☐ Control Panel

NOTES

BILLING SETTINGS

Rate Table: RT ORIG

Tax Profile:

Routing Plan:

Activation Fee: 0 USD

Maintenance Fee: 0.25 USD every 24 hours

EXPIRATION SETTINGS

Expire date:

Expire period: day(s)

OK

Cancel

Apply

 **Attention**

**The Calling Cards feature works only via RADIUS-protocol**, so to make use of it, you need to have RADIUS enabled. You may also use a specific platform that is able to handle calling card series authorization, for example, **Mera IP Centrex** or **Quantum Tenor DX** (class 5 switch).