Calling Cards

In this article

- Section overview
- Advanced Search
- Creating a Card Series
- Calling Cards Series Properties

Section overview

This section represents a built-in calling cards generator that allows you to create or change cards series for prepaid customers. Each generated card is considered a billing client, so a customer can perform calls, log in to their client panel to browse statistics and other relevant information.

Screenshot: Calling Cards section main window

Column	Description	
Status	A name that describes current cards series	
		Indicates that cards series is ***active***
		Indicates that cards series is ***stopped***
		Indicates that cards series is ***deleted***
Number of Series | Name of Series	A code of cards series and its name (if indicated). This code will prepend a serial number (only numeric, up to 100,000,000)	
Balance	Cards balance value within a current series	
Qty	Quantity of cards within a series	
Reseller	Name of a reseller, who owns a cards series	
Rate Table	Rate table applied to respective cards series	
Act. Fee	Price of cards series activation fee	
Maint. Fee	Fixed charge for activated cards within a series	

Advanced Search

In the top right corner of the section above the table, the **Advanced Search** drop-down menu is located. By clicking on a red downwards arrow icon (calling cards in the section are filtered by ***Active*** status and ***All resellers*** by default), the following drop-down menu is displayed:

Screenshot: Advanced Search drop-down menu



To apply the specified search criteria, click the **Search** button; to cancel the applied parameters, click **Reset**.

Creating a Card Series

To create a card series, click the **New Cards Series** button and a new window with settings will pop-up:

Screenshot: Generate cards series window



Field	Description
Series Name	Indicate a name for a cards series
Series Number	Define a code of a cards series. This code will prepend a serial number (only numeric, up to 100 000 000). For example, if the ***Series Number*** is ***45***, the cards number will start with 45: ***45-001122333, 45-001122334*** and so on.
Balance	Specify the cards balance value within a current series
Quantity	Set the number of calling cards within a current series
PIN Length	Specify a PIN-code length for a current calling cards series (it can be no less than 8 digits)
Status	Define an initial status of created calling cards within a series. Can be changed later in cards series settings

Control Panel checkbox	Defines whether calling cards users can log in to their control panels or not. If enabled, a user can log in to the control panel by using the card serial number as login and a PIN-code as password
Notes	Indicate additional information regarding a cards series (optional)
Rate Table	Define a rate table for all cards within a series. This field is mandatory
Tax Profile	Select a respective tax profile that will be used for billing settings
Routing Plan	Select a routing plan for a current cards series
Activation Fee	Enter an activation fee in this field (if necessary)
Maintenance Fee	Define a charged fee each X hours for all activated cards
Expiration date	Current calling cards series will be expired on a specified date
Expiration period	When a specified number of days passes, starting from activation date, a current calling cards series will be expired

After specifying all necessary fields, click **OK** and a new cards series will be created.

Calling Cards Series Properties

To open series properties, click ***Series Number***, and you will be displayed a table of calling cards with the following columns:

Screenshot: Cards List tab



Column	Description
Status	Status of a card within a current series. There are **4** possible statuses: ***activated, pending, expired, used***
Number	Number of a card within a current series
Balance	Balance of a respective calling card
PIN	Respective calling card PIN-number

1. You can export the whole card series to an **.xls** file by clicking the **Download XLS** icon (see screenshot above).
2. You can use the **Advanced Search** drop-down menu to find a card by clicking on a blue downwards arrow icon in the right-hand corner of the page (see screenshot above).

To change the previously entered parameters while creating a series, please open the **Edit Cards Series** tab.

Screenshot: Edit Cards Series tab



Attention

The Calling Cards feature works only via RADIUS-protocol, so to make use of it, you need to have RADIUS enabled. You may also use a specific platform that is able to handle calling card series authorization, for example, **Mera IP Centrex** or **Quintum Tenor DX** (class 5 switch).